



- DC-DC Converter Apps: Forward w/ Active or Resonant Reset | ZVT Full Bridge
- Power Rating 100-300W Typical w/ Forward Topology & 200-750W ZVT Full Bridge
- Frequency Range: 100 Khz to 800 Khz Typical
- Patent Pending Planar Winding – “Heat Spreader” – Unique Thermal Interface

Part #	Pri T	SecT	Pri Induct μH (Nom)	Pri DCR mΩ	Sec DCR mΩ	Leakage L (μH)	Inter-leave	Max Height (mm)
PK-28-1-8001	28	1T	2560	210	0.50	0.65	Double	10.4
PK-22-1-8002	22	1T	1580	160	0.50	0.50	Double	10.4
PK-20-1-8003	20	1T	1300	132	0.50	0.45	Double	10.4
PK-14-1-8004	14	1T	640	78	0.50	0.30	Double	10.4
PK-5-1-8005	5	1T	82	4.0	0.35	0.25	Double	10.4
PK-4-1-8006	4	1T	54	2.4	0.35	0.18	Double	10.4
PK-3-1-8007	3	1T	30	1.8	0.35	0.10	Double	10.4

Notes: Operating Temp. -30°C to +130°C | Primary to Secondary Isolation 1500 Vdc Basic

